



USER MANUAL

HDMI to DP Converter (8K@30Hz)

Enjoy the vivid world

Introduction :

This HDMI to DP converter can convert high-definition HDMI signal to DP signal output, HDMI input resolution support up to 8K@30Hz; DP output resolution support up to 8K@30Hz. Plug and play, convenient and reliable, Suitable for HDMI to DP signal or DP interface display equipment, etc.



Features :

- * Support HDCP2.3 , DP1.4a;
- * Support 8K@60Hz with compression data (bypass mode);
- * HDMI input support up to 8K@30Hz, compatible with 4K@120Hz and below resolution;
- * DP output support up to 8K@30Hz, compatible with 4K@120Hz and below resolution;
- * Support HDR10, FEC, VRR, Visually realistic and perfect;
- * No software driver, plug and play;
- * Product shape is small and beautiful.

Specifications:

HDMI resolution	up to 8K/30Hz
Support color format	RGB/YCbCr
Support audio format	DTS-HD/Dolby-trueHD/DTS/Dolby-AC3/DSD

Input cable distance	8K/30Hz ≤3M AWG24 HDMI standard cable
Output cable distance	8K/30Hz ≤2M DP standard cable
HDMI Input	1
DP Output	1
Max working voltage	DC/5.5V
Max working current	420mA
Operating Temperature range	(-15 to +45 °C)
Operating Humidity range	5 to 90%RH (No Condensation)
Dimension (L x W x H)	63x27x15 (mm)
Weight	15g

Connection Diagram :



Operating and Connecting :

1. Connect HDMI source devices and input of Converter with HDMI cable.
2. Connect display devices and output of Converter with DP cable.
3. Connect 5V Power to the HDMI to DP Converter with Micro USB cable.

Accessories :

- | | |
|-------------------------|-----|
| 1、 HDMI to DP Converter | 1PC |
| 2、 Mini DP to DP cable | 1PC |
| 3、 Micro USB cable | 1PC |